

BRADLEY ENGINEERING

Hollybush Farmhouse, Lymington Road, Brockenhurst, Hampshire. SO42 7UF Tel:01590 622440

BE_HD10 RCP



Rugged, Simple, Flexible

The Mini RCP is configured to control all the functions of the BE_HD10 camera. All the camera functions can be accessed from the RCP including Zoom, Iris, Focus, Scene Files and Power up memory.

The unit outputs both **RS485** and **RS232c** which can be sent either directly to the camera or via a Bradley Engineering Protocol Converter or Joystick Controller. Using the RS485 option enables 4 cameras to be controlled from one RCP over a cable length of up to 1km.

Main Functions

Iris
Gain, Shutter, Detail
Red Gain, Blue Gain
White Balance - Auto, AWB, 3K2, 5k6, SceneA, SceneB,
Zoom, Focus
Update, Display
Camera Select - 1, 2, 3, 4

Sub Functions

Connected Device - Camera, RS485
Gamma
Digital Zoom, Auto Focus, Auto Iris
Format; 4:3, 16:9, NTSC, PAL, 720p/50, 720p/59.94, 1080i/50, 1080i/59.94
Power Up memory - Set, Cancel

Power: 12v, 200mA
Dimensions: L.210mm, W.102mm, D.35mm